

# LARDIS

## How do I perform a factory reset on LARDIS:ONE 7 (Garmin)?

The following steps are necessary for this:

### Prerequisite:

- Fully charge the battery.
- LARDIS:ONE software version min. version 2.0
- If necessary, configuration exported.

### Execution Reset:

- Long press on the gear icon -> call up device settings.
- Call up "About the device" -> "Garmin device information".
- Press "Device ID" several times until the overlay "Additional settings are available" appears.
- 2x back to the settings level.
- Call up "Save & reset" -> select "Reset to factory settings" and confirm accordingly.
  
- Device is reset...
- After a restart, please confirm the end user licenses and select language.
- Open device settings and go to "About the device".
- Press "Build number" several times until "You are now a developer" is displayed.
- 1x back to the settings level and call up "Developer options" there.
- Activate "USB debugging" there.

### Reinstall / license LARDIS:ONE v2.x:

- Connect LARDIS:ONE to a PC via USB.
- Call up LARDIS:ONE Setup and restore the license.
- Install the LARDIS:ONE update.
- Import configuration / set up again.
- Press the home button on the device and always confirm "LARDIS Launcher" as the start page.

**i** Until version **2.2.3**

The map application cannot be started (anymore) after a reset from the LARDIS:ONE interface. [Here](#) you can find the solution.

Unique solution ID: #1109

Author: Tech. Support

Last update: 2023-02-10 15:49